

A Blend of Solvents designed to remove flux residues from PCB's

Applications:

- Removal of flux residues from PCB's and components
- Evaporates quickly leaving no residue
- Fast and effective in use
- Also removes uncured surface mount adhesive

Directions:

Spray from a distance of 25 – 30cm liberally onto the area to be cleaned, allow to run off and leave to dry. For heavy deposits further re-application may be required

Note:

May affect some plastics. If unsure test a small area before general use.

Not for use on live electrical equipment. Allow solvent to evaporate completely before turning on power supply.

Technical Data

Appearance	Clear, colourless liquid
Odour	Sweet, solvent
SG at 25°C	0.66
Discharge rate	1.1g/second
Flammability	Classified as extremely flammable under current EC regulations
Flashpoint	Not applicable in sealed aerosol
Pack size	400ml

Storage: This product may be stored at normal temperatures and has a shelf life of not less than 36 months with correct storage. Aerosols should always be stored below 50°C, away from direct heat and naked flames